

CS 275 Control panel

- 6 fully programmable zones
- Wireless expansion up to 16 zones
- Integrated dialler
- 20 customisable pre-configured zone types
- 40 user codes
- 1 duress code
- Up/downloadable with competitor lockout
- 2 true partitions
- 4 on-board outputs
- Walk test mode
- 2-wire or 4-wire smoke detectors
- Automatic arming with auto retry
- Siren supervision
- Answering machine defeat
- Dynamic battery test
- Voltage and current telephone line monitor
- Built-in siren driver/voltage out
- Assign zones to one or multiple partitions
- Maximum 8 keypads per partition



→ Communication

Events are reportable to 6 phone numbers and are selectable by partition and/or event.

- SIA and Contact ID formats
- Supports all major formats
- Flexible autotest reports
- Failure to communicate reporting
- Reports entering/exiting programme mode
- Will communicate alarm events during programming

→ 256 event log

- Includes date, time, event and partition number.

→ Partitioning

- 2 true partitions
- Separate account code for each partition
- User code assignment to multiple partitions

→ Wireless zone expansion

The CS 275 can be expanded using an 8 or 16 zone wireless receiver.

- Up to 16 supervised wireless zones
- Keypad annunciation of alarm, tamper, low battery & lost transmitter

→ System expansion modules for the CS 275 * Maximum 3 modules per control panel

Wireless expansion module

Wireless receivers allow the integration of the most advanced wireless technology with the CS 275. Up to 16 transmitters can be individually displayed at the keypad for alarm and all supervisory reports. The receiver can be mounted in the panel housing or remotely.

CS 507 - 7 output module

Flexible mapping from a large library of events or combination of events allows the CS 507 to become the director of lights or home automation with either X-10 or other power outputs.

This module also allows multiple scheduling possibilities such as auto-arming, holiday planning and opening/closing time.

Home systems audio module

The CS 534 home systems module can be used to control X10 devices and allows two-way voice/listen-in functionality.

With available add-on modules to accommodate enhancements such as wireless integration, X-10 home automation and two-way voice the CS 275 provides flexible expansion capabilities for mid-size installations.

CS 275

→ Technical data

Operating power	16.5 V ac, 25 VA
Auxiliary power with 25 VA transformer	500 mA
Loop resistance	
For standard loop	4K7 end-of-line
For 2-wire smokes	30 Ohm maximum
Built-in siren driver	2-tone (temporal & yelp) - for internal siren only
Alarm current available (if siren driver is not used)	2.5 A
Loop response	500 ms
Operating temperature	0° to 49° C
Dimensions - keypad (LCD/LED)	10 x 14.5 cm
Housing	25 x 25 cm
Colour	
Keypad	White; ABS
Housing	Off white

→ How to order

CS 275M	6 zone control panel - metal housing
CS 5xx8*	LCD keypad
CS 5xx6*	LED keypad
CS 534	Audio board with X-10
CS 3510	Loudspeaker/microphone unit for CS 534
CS 507	Output expander
CS 5003	Upload/download software

*xx - Depending on country

Interlogix UK Limited

Unit 5, Ashton Gate,
Ashton Road, Harold Hill,
Romford, Essex RM3 8UF
Tel. 01708-381496
Fax 01708-381371

Interlogix Ireland Limited


Taurus Business Centre
Greenhills Road
Tallaght, Dublin 24
Tel. 01-459.97.60
Fax 01-452.74.48

Interlogix Europe & Africa

Headquarters
Excelsiorlaan 28
B-1930 Zaventem
Tel. 02-725 11 20
Fax 02-721 40 47

Sales Offices : Austria, Baltic States, Belgium, Czech Republic, Denmark, Eastern Europe, France, Germany, Greece, Hungary, Ireland, Italy, Netherlands, Norway, Poland, Portugal, Slovak Republic, South Africa, Spain, Sweden, U.K.

LFCS275 03 Rev.1 0501/UK

 Aritech reserves the right to change specifications without notice.
Aritech is a trademark of Interlogix B.V.