

## TX-3011-03-2

Paniekknop, 868 MHz Gen2, zwart

### Paniekknop, 868 MHz Gen2, zwart

---

Deze sensor is een bewaakte, draadloze hold-up of panieknop en kan rond de nek gedragen worden met behulp van het meegeleverde halssnoer. De sensor bevat twee activeringsknoppen. Een alarm wordt geactiveerd door het indrukken en het ingedrukt houden van beide knoppen en dit gedurende minimum een halve seconde. De LED op de sensor knippert gedurende een minuut na het activeren van het alarm. De sensor is eveneens waterdicht.

The sensor is a supervised, wireless hold-up or panic device and can be worn around the neck using the strap provided. The sensor contains two activation buttons. An alarm is activated by pressing and holding both buttons for a minimum of half a second. The led on the sensor flashes for one minute following the alarm activation. The sensor is water resistant.



### Kenmerken

---

- Learn-mode technologie
- Learn-mode technology
- Activering door gelijktijdig indrukken van 2 knoppen
- 2 button activation
- Supervised
- Bewaakt
- Worn around neck using the strap
- Wordt rond de hals gedragen d.m.v. meegeleverd halssnoer
- LED to confirm alarm activation
- LED om alarmactivering te bevestigen

# TX-3011-03-2

Paniekknop, 868 MHz Gen2, zwart

## Technische gegevens

General	
Batterijtype	1 x 3 V Lithium
Type	Pendant
Levensduur van de batterij (typisch)	3 jaar
Water resistent	No
Werkingsfrequentie	868 MHz
Compatibel met	UTC 868 MHz Gen2 ontvangers
Wired/wireless	
Bereik in open lucht	150 m
Wired-Wireless	Wireless
Afmetingen (L x B x H)	
Wireless frequency	868 MHz AM
Open-air range	150 m
Electrical	
Batteries	1 x 3 V lithium battery
Battery lifetime	3 years
Physical	
Physical dimensions	64 x 46 x 13 mm
Colour	White
Battery type	1 x 3 V Lithium
Battery lifetime (typical)	3 years
Operating frequency	868 MHz
Compatible with	Interlogix 868 MHz Gen2 receivers
Open-air range	150 m
Dimensions (L x W x D)	64 x 46 x 13 mm

## Bestelinformatie

Type nummer	Omschrijving
TX-3011-03-2	Paniekknop, 868 MHz Gen2, zwart
TX-3011-03-2	
TX-3011-03-2	2 button panic 868 MHz Gen2, black
TX-3011-03-1	Paniekknop, 868 MHz Gen2, wit
TX-3011-03-1	
TX-3011-03-1	2 button panic 868 MHz Gen2, white