

## RF-KF101-K4

### 2-way keyfob LoNa

This 4-button 2-way keyfob, using the latest LoNa technology, allows the end-user to arm, disarm or partially arm their system without having to memorize access codes or race to beat entry or exit delays.

Each button press will be indicated by a blinking LED and the acknowledgement coming from the receiver will also trigger the LED on the keyfob.

In case the system is not ready to arm, or in case the end-user is out-of-range of the receiver, this will also be visible on the keyfob when pressing a button. Even a system in alarm, will be indicated when performing a button press.

It offers one additional programmable buttons which can be used e.g. to turn on and off lights before entering the premises, activate an automated garage door, etc.

It can also be used to send a panic alarm by pressing the lock and unlock buttons simultaneously, or to trigger an auxiliary alarm by pressing the "1" and "2" button simultaneously.



#### Standard Features

- Using LoNa technology
- Compact, robust, premium design
- · LED confirmation of sent and received messages
- Out-of-range LED indication
- 1 programmable button
- Panic and Auxiliary alarm functionality available
- 5 years of battery life (based on usage)
- . EN & Incert security approvals

# RF-KF101-K4

### 2-way keyfob LoNa

### **Specifications**

Compatibility	Interlogix LoNa transceivers (e.g. ZeroWire)
Wireless operating frequency	433.65 MHz
Power output	-9 dBm EIRP
Battery type	3V lithium CR2032
Battery life	5 years
Power supply type	EN50131-6:2008 Type C
Housing	EN 50131-3:2009 ACE Type B, portable
Operating environment	
Temperature	0 to 49°C (32 to120°F)
Relative humidity	5 to 95% noncondensing
Product weight	42.5 g
Product dimensions	32 x 13 x 63 mm

### **Ordering Information**

Part No.	Description
RF-KF101-K4	2-way keyfob LoNa

